



8 STARTER IS SHIPPED WITH 480VAC TRANSFORMER PRIMARY FUSING.
FOR 240VAC APPLICATION REMOVE FU4 & FU5 0.4A FUSES,
REPLACE WITH 0.8A FUSES AND JUMPER PER TRANSFORMER LABEL ON BASE
FOR 240VAC.



CB1	-	CIRCUIT BREAKER, 15A, 480V, 3PH, 35KAIC
CBH	-	FRONT MOUNT ROTARY OPERATOR FOR UTE100 CIRCUIT BREAKERS, TYPE 3/3R/4, 12INCH SHAFT
M1	-	CONTACTOR, 12A, NEMA 0, 120V, 50/60HZ COIL, 1NO/1NC
O/LN1	-	OVERLOAD RELAY, ELECTRONIC, CLASS 1-30, 4 - 22A
ENCL	-	ENCLOSURE, FREESTANDING, TYPE 4, 20"H x 16"W x 8"D
FU4,5	-	CONTROL FUSES (PRIMARY SIDE), TIME DELAY, 0.4A, 600V, 200KA CLASS CC
FU6	-	CONTROL FUSES (SECONDARY SIDE), TIME DELAY, 0.8A, 500V, 10KA
TB1	-	CONTROL TERMINAL BLOCK
TB2	-	CONTROL TERMINAL BLOCK
TB2	-	CONTROL TERMINAL BLOCK
T1	-	CONTROL TRANSFORMER, 75VA, 480V PRIMARY - 120V SECONDARY
PB1	-	START PUSHBUTTON, 30MM, FLUSH GREEN, W/ N.O. CONTACT
PB2	-	STOP PUSHBUTTON, 30MM, RAISED RED, W/ N.C. CONTACT
PB3	-	0/L RESET PUSHBUTTON, 30MM, FLUSH BLACK, W/ N.O. CONTACT
LT1	-	RUN PILOT LIGHT, 30MM, ILLUMINATED, 120V, RED
SW1	-	H-0-A SELECTOR SWITCH, 30MM, 3-POSITION, W/ N.O./N.C. CONTACTS



REVISIONS DO NOT SCALE DWG	THIRD ANGLE PROJECTION		UNLESS OTHERWISE SPECIFIED ALL DIMENSIONS IN INCHES INTERPRET DRAWING PER ASS. Y14.5M-1994 TOLERANCES: .XX ± .03 .XXX ± .015 ANGLES ± 1'	TITLE: ENCLOSURE LAYOUT CBRC12-N0-3R NEMA SIZE 0 STARTER 480/240VAC LINE CPT, ELECTRONIC O/L START, STOP, RESET P/S RUN LT, H-O-A SW	SIGNATURES	DATE	 BENSHAW 615 ALPHA DRIVE PITTSBURGH, PA 15236 550 BRIGHT STREET LISTOWE, ONTARIO H4W 3H3	REV 0
	THIS DRAWING AND ALL INFORMATION CONTAINED HEREIN, IS THE PROPERTY OF BENSHAW INC., AND MAY NOT BE REPRODUCED, OR DIVULGED TO UNAUTHORIZED PERSONS WITHOUT THE EXPRESS WRITTEN CONSENT OF BENSHAW INC. IT IS PROVIDED SOLELY FOR THE CONVENIENCE OF THE USER, AND SHALL BE RETURNED UPON REQUEST.	MATERIAL: FINISH:	CHKD. TJR 06/05/20 CHKD. MSN 06/15/20 ENG. MSN 06/15/20 MFG.		DWG NO.	SCALE: 3"=1'-0		

