

# PREPACKAGED FULL VOLTAGE STARTERS WITH DOOR-MOUNTED CONTROLS



## CBRC12 SERIES – COMBINATION / NEMA 12/3R / OVERLOAD PROTECTION

- NEMA 12/3R enclosure
- cUL listed
- NEMA rated contactor and separately mounted electronic class 20 protection relay
- 480/240:120 fused control power transformer
- Units set up to have 240 VAC fuses shipped loose with unit
- Labels for 480 and 240 installed
- Door-mounted start and stop push-buttons
- Door-mounted overload reset push-button
- Red run indicator light
- (2) Auxiliary contacts
- Hand-off-auto selector switch
- Ground lug
- Terminal block



### CBRC12 - 230VAC OR 460VAC

Model Number	Footnote	NEMA Size	NEMA Horsepower				Dimensions (in.)		
			230VAC	FLA at 230VAC	460VAC	FLA at 460VAC	H	W	D
CBRC12-N00-3R-HB	1	00	1	4.2	2	3.4	20	16	8
CBRC12-N0-3R-HB	1	0	3	9.6	5	7.6	20	16	8
CBRC12-N1-3R-HB	1	1	5	15.2	10	14	20	16	8
CBRC12-N2-3R-HB	1	2	10	28	25	34	20	16	8
CBRC12-N3-3R-HB	1	3	25	68	50	65	24	20	10
CBRC12-N4-3R-HB	1	4	50	130	100	124	36	24	12
CBRC12-N5-3R-HB	2	5	100	248	200	240	48	24	12
CBRC12-N6-3R-HB	2	6	200	480	400	477	48	36	16

- 1) Web stocked.
- 2) Built to order - Please allow one week for shipment.

**BENSHAW, Inc.**  
615 Alpha Drive, Pittsburgh, PA 15238, United States  
Phone: 412.968.0100

**BENSHAW Canada Controls, Inc.**  
550 Bright Street East, Listowel, Ontario N4W 3W3  
Phone: 519.291.5112

**Benshaw, Inc.**

615 Alpha Drive  
Pittsburgh, PA 15238 United States  
Phone: +1 412-968-0100

**Benshaw Canada Controls, Inc.**

550 Bright Street East  
Listowel, Ontario N4W 3W3 Canada  
Phone: +1 519-291-5112

**AuCom**

*An Amconex Group Company*  
Germany

New Zealand

Dubai

South Korea

China

**For more information and your local contact visit [www.benshaw.com](http://www.benshaw.com)**



**BENSHAW**

*Applied Motor Controls*

AN AMCONEX GROUP COMPANY